



subject: **Changes to enter/change threshold**

date: **October 21, 1996**

from: **BNS-2000 Customer Support
1800WE2CARE**

PRODUCT DOCUMENTATION NOTICE

This memo describes changes made to the **enter threshold**, and **change threshold** commands in BNS-2000.

The **P-BIT PARITY CODE VIOLATIONS**, **ERRORED SECOND** and **SEVERELY ERRORED SECONDS** prompts will now use the same value for both the receive and transmit directions. The descriptions of these prompts should be modified to indicate these prompts will use the value entered for the receive and transmit direction thresholds.

Because the original database supplies default threshold profiles which cannot be changed a new command **dvchange threshold** has been added. The syntax for that is as follows.

```
CC0> dvchange
OBJECTS [smdsnode, threshold]: threshold
DEFAULT THRESHOLD PROFILE ID (0=t1, 1=t3, 2=e1, 3=e3) [0-3]: 1
TUNE T3 15 MINUTE INTERVAL PARAMETERS [yes, no: +(no)]: yes
TUNE T3 24 HOUR INTERVAL PARAMETERS [yes, no: +(no)]: yes
DEFAULT THRESHOLD PROFILE ID (0=t1, 1=t3, 2=e1, 3=e3) [0-3]:
```

This PDN modifies product document Data Networking Products Commands Reference, CIC ID 255-100-234 (Issue 1), pages 4-259, and 4-265 through 4-273.